

## Modifying the Netopia for LAN-ISDN Service

### Changing the Dial Up Phone Number

Our internet access phone numbers can be retrieved via e-mail at numbers-info@psi.com or via our FaxBack server by dialing 518-283-8860 and choosing option 4. Follow the prompts, select code number 1002, and key in your fax number. **Please be sure to check with your telephone company to insure it is a local call, as long distance charges will apply and be your sole responsibility.**

Use the arrow keys to move the cursor within the menus. With the field highlighted you may change it, then hit enter to accept. Esc will cancel or if you're in a sub menu it will return you to the previous menu.

From the Main Menu choose:

Easy Setup...

then select NEXT SCREEN to reach the following screen:

```
Connection Profile 1: Easy Setup Profile

Connection Profile Name:      Easy Setup Profile
Number to Dial:              19103332366
Remote IP Address:           38.1.1.1
Remote IP Subnet:            255.0.0.0

PPP Authentication (Security)... PAP

Send User Name:              LI0CSG
Send Password:               *****
Receive User Name:
Receive Password:

PREVIOUS SCREEN              NEXT SCREEN
```

Using the arrow keys, move to the phone number field, make your change and hit enter.

Select NEXT SCREEN on each menu until you see RESET DEVICE. Select it and hit enter. This will save your change(s) and restart the router.

## Modifying the Netopia for LAN-ISDN Service

### Forcing the Farallon Netopia to Dial

From the Main Menu select: Statistics, Utilities, Tests

```

                                Statistics, Utilities, Tests

    Statistics      General Statistics...
                   Event Histories...
                   Routing Tables...

    Utilities      Date and Time...
                   Establish WAN Connection...
                   Disconnect WAN Connection...

                   Ping...
                   Upgrade Feature Set...
                   Restart System...
                   Revert to Factory Defaults...

    Tests          ISDN Switch Loopback Test...

    Select the profile with the gateway of 38.1.1.1 and hit Enter:
    
```

```

                                Statistics, Utilities, Tests
    +-Profile Name-----IP Address----IPX Network--+
    +-----+
    Statisti | Net          38.1.1.1
    Utilitie |
    Tests    |
    +-----+

    At the next screen, you should see the Netopia dialing. It should look like this:
    
```

```

                                Call Status

    Profile Name -- Net
    Connection State -- Dialing

    Channel B1 State -- Acquiring

    Channel B2 State --
    
```

Hit ESCAPE to return to previous menu.